

YOUR DVR INFO: (keep for your records)

User ID:

Password:

PORT:

STATIC IP:

GROUP ID:



How to Set up Remote Monitoring of your DVR

STEP 1

Install **Control Center** from the CD provided by installers, or by downloading the latest version from <http://www.spytechsurveillance.com/support.html>

You will find 3 new icons on your desktop

-**Control Center Monitor**

-**Control Center Playback**

-**Control Center Configuration Tool**

STEP 2

Launch Control Center **Monitor**

The Login prompt will come up, type:

User Name: **Administrator**

Password: **admin**

STEP 3

Go to the **My Units**, right click and select **Add Unit**

If You Are On the Local Network Same As The DVR:

If you are on location and connected to the same network as the DVR, you will notice the DVR unit's IP address appears under the **Local Area Units**. Drag that up to **My Units** and an Add Unit dialog window will pop up, enter in your user ID and password and hit **OK**.

If You Are Away and Have a **STATIC IP addressed Unit At the DVR Site:**

Go to My Units, right click and select **Add Unit**. Select Static IP. Input your IP **Address** in box. Click **PORT**, input your port number. Click the **Find** button.

The DVR's information will appear in the window.

Enter in your user ID and password and hit **OK**.

If You Are Away and Have a **DYNAMIC IP addressed Unit At the DVR Site:**

Go to My Units, right click and select **Add Unit**. Select **Dynamic IP Address**. Type in the **Registration Server** IP address **210.116.114.37**. Go to the right and type in your unique **GROUP ID** in the box to the left of **Find By Group ID** and then click on it. Select the found IP address in table below and click on the Find button.

The DVR's information will appear in the window. Enter in your user ID and password and hit **OK**.

Recommended Options Settings:

In Control Center Monitor, go to Tools/Options/Display:

- 1) Monitor Viewer Mode: Set to (Full)
- 2) Bandwidth Adjustment: Set to (Off)